The top half of the page features a complex, abstract background of overlapping, semi-transparent blue triangles and polygons in various shades of blue, creating a dynamic, crystalline effect. This pattern transitions into a white background at the bottom.

Technical Reference
020-102782-01

4K7-HS and 4K10-HS

Serial Commands

CHRISTIE®

NOTICES

COPYRIGHT AND TRADEMARKS

Copyright © 2019 Christie Digital Systems USA Inc. All rights reserved.

All brand names and product names are trademarks, registered trademarks or trade names of their respective holders.

GENERAL

Every effort has been made to ensure accuracy, however in some cases changes in the products or availability could occur which may not be reflected in this document. Christie reserves the right to make changes to specifications at any time without notice. Performance specifications are typical, but may vary depending on conditions beyond Christie's control such as maintenance of the product in proper working conditions. Performance specifications are based on information available at the time of printing. Christie makes no warranty of any kind with regard to this material, including, but not limited to, implied warranties of fitness for a particular purpose. Christie will not be liable for errors contained herein or for incidental or consequential damages in connection with the performance or use of this material. Manufacturing facilities in Canada and China are ISO 9001 certified. Manufacturing facilities in Canada are also ISO 14001 certified.

WARRANTY

Products are warranted under Christie's standard limited warranty, the complete details of which are available by contacting your Christie dealer or Christie. In addition to the other limitations that may be specified in Christie's standard limited warranty and, to the extent relevant or applicable to your product, the warranty does not cover:

- a. Problems or damage occurring during shipment, in either direction.
- b. Problems or damage caused by combination of a product with non-Christie equipment, such as distribution systems, cameras, DVD players, etc., or use of a product with any non-Christie interface device.
- c. Problems or damage caused by misuse, improper power source, accident, fire, flood, lightning, earthquake, or other natural disaster.
- d. Problems or damage caused by improper installation/alignment, or by equipment modification, if by other than Christie service personnel or a Christie authorized repair service provider.
- e. Use of third party product enclosures for environmental protection during outside use must be approved by Christie.
- f. Problems or damage caused by use of a product on a motion platform or other movable device where such product has not been designed, modified or approved by Christie for such use.
- g. Except where the product is designed for outdoor use, problems or damage caused by use of the product outdoors unless such product is protected from precipitation or other adverse weather or environmental conditions and the ambient temperature is within the recommended ambient temperature set forth in the specifications for such product.
- h. Defects caused by normal wear and tear or otherwise due to normal aging of a product.

The warranty does not apply to any product where the serial number has been removed or obliterated. The warranty also does not apply to any product sold by a reseller to an end user outside of the country where the reseller is located unless (i) Christie has an office in the country where the end user is located or (ii) the required international warranty fee has been paid.

The warranty does not obligate Christie to provide any on site warranty service at the product site location.

PREVENTATIVE MAINTENANCE

Preventative maintenance is an important part of the continued and proper operation of your product. Failure to perform maintenance as required, and in accordance with the maintenance schedule specified by Christie, will void the warranty.


REGULATORY

The product has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the product is operated in a commercial environment. The product generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of the product in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at the user's own expense.

CAN ICES-3 (A) / NMB-3 (A)

이 기기는 업무용(A급)으로 전자파적합등록을 한 기기이오니 판매자 또는 사용자는 이점을 주의하시기 바라며, 가정 외의 지역에서 사용하는 것을 목적으로 합니다.

ENVIRONMENTAL

The product is designed and manufactured with high-quality materials and components that can be recycled and reused. This symbol  means that electrical and electronic equipment, at their end-of-life, should be disposed of separately from regular waste. Please dispose of the product appropriately and according to local regulations. In the European Union, there are separate collection systems for used electrical and electronic products. Please help us to conserve the environment we live in!

Content

Communicating with 4K7-HS and 4K10-HS.	7
Connecting to the projector RS232 IN port.	7
Connecting to the projector Ethernet port.	7
RS232 communication parameters.	7
Correct command formatting.	8
Understanding message format.	8
Message structure.	8
Error messages.	9
Serial API commands.	10
ADR–Projector Address.	10
APW–Auto Power On.	10
ASH–Auto Shutdown.	11
AWF–Auto Warp Filter.	11
BDR–Baud Rate.	12
BGC–Base Gamma Curve.	12
BOG–Blue Gain.	13
BOO–Blue Offset.	13
BRT–Brightness.	14
CCA–Color Matching.	14
CCI–Color Temperature.	16
CEL–Ceiling Mount Setting.	17
CNR–4-Corner Geometry Correction.	17
CON–Contrast.	18
CSP–Color Space.	18
CWI–Wheel Index Setting.	19
DEF–Factory Defaults.	19
DIM–Contrast Enhancement.	20
DSH–Digital Horizontal Shift.	20
DSV–Digital Vertical Shift.	21
DTL–Detail.	21
DZH–Digital Horizontal Zoom.	21
DZV–Digital Vertical Zoom.	22
EBL–Edge Blending.	22

ERR–Error Log. 24

FAN–Fan Info. 24

FCS– Focus. 25

FCT–Serial Number. 25

FDY–Frame Delay. 25

FKC–4K Compatible. 26

FRZ–Image Freeze. 26

GOG–Green Gain. 26

GOO–Green Offset. 27

GOR–RGB Gain/Offset Reset. 27

HAR–Reset Hue, Saturation, and Gain to Default. 28

HAT–High Altitude. 28

HDR–HDR. 28

HKS–Hot Key Settings. 29

HOR–Horizontal Position. 30

HPC–Horizontal Pincushion. 30

HSG–Color Enhancement. 31

ICI–Communications Info. 31

ILI–Light Source Info. 32

IRC–IR Control. 32

ITP–Test Pattern. 33

KBL–Keypad Backlight. 33

KEY–Key Mode Emulator. 34

LCB–Lens Motor Calibration. 34

LCE–Last Serial Command Error. 35

LDI–Laser Diode Information. 35

LET–Lens Type. 36

LHO–Lens Shift Horizontal. 36

LLM–Low Latency Mode. 37

LRR–L/R Reference. 37

LMA–Lens Memory Apply Position. 38

LMS–Lens Memory Save Current Position. 38

LOC–Localization Language. 38

LOL–Lights Out Signal Level. 39

LOT–Lights Out Timer. 39

LPM–Light Source Mode. 40

LPP–Constant Power. 40

LSE–Last System Error. 41

LVO–Lens Shift Vertical. 41

MBE–Message Box Enable.	41
MIF–Main (Single) Source Information.	42
MMC–Motion Estimate and Motion Compensation.	42
MSH–Menu Shift Horizontal.	43
MSV–Menu Shift Vertical.	44
MTO–Menu Time Out.	44
MWF–Manual Warp Filter.	45
NET–Network Setup.	45
NTW–Wireless Network.	46
OSD–On Screen Display.	47
OST–OSD Transparency.	47
PCG–Change Pin.	48
PHS–Picture-in-Picture Horizontal Size.	48
PIF–Projector Information.	48
PIP–Picture in Picture.	49
PIV–PIN Protect.	50
PPP–Main Layout.	50
PPS–Picture-in-Picture/Picture-by-Picture Swap.	51
PST–Picture Setting.	51
PWR–Power.	52
RLC–Light Sensor Calibration.	53
ROG–Red Gain.	53
ROO–Red Offset.	53
SBL–Status LED.	54
SEC–Serial Port Echo.	54
SHU–Shutter.	55
SIF–Secondary Source Information.	55
SIN–Select Input.	56
SIV–Serial Command Version.	57
SKS–Source Key Function Settings.	57
SLP–Sleep Timer.	57
SNS–Source Name Setting.	58
SOR–Rear Projection.	58
SOS–3D Sync Out.	59
SPP–Serial Port Path.	59
SPS–Splash Screen.	60
SST–Projector Status.	60
SZP–Size Presets.	60
TDE–3D Enable.	61

TDI-3D Invert.	62
UID-Enter Service Mode.	62
VPC-Vertical Pincushion.	62
VRT-Vertical Position.	63
WAP-Apply Warp Settings.	63
WAS-Save Warp Settings.	64
WPK-White Peaking.	64
WRE-Warping Reset.	65
WRP-Geometry Correction.	65
ZOM-Zoom.	65

Communicating with 4K7-HS and 4K10-HS

Understand the information and procedures for communicating with 4K7-HS and 4K10-HS from a remote location.

You can communicate with the projector through the RS232 IN port or the Ethernet port. When connecting the projector to a computer, use a direct connection. Docking ports can cause software upgrade failures.

Connecting to the projector RS232 IN port

Communicate with the projector through the RS232 IN port.

1. Connect one end of a null standard nine-pin female to female modem cable to the projector RS232 IN port.
2. Connect the other end of the null standard nine-pin female to female modem cable to a computer.
3. Connect PIN 2 to PIN 3, PIN 3 to PIN 2 and PIN 5 to PIN 5.

Connecting to the projector Ethernet port

Communicate with the projector through the Ethernet port.

1. Connect an Ethernet cable to the projector from your computer.
2. Setup the correct IP for the projector on your computer.
3. On the TCP software, use port 3002.
4. Start sending serial commands.

RS232 communication parameters

The RS232 IN port has several communication parameters.

Parameter	Value
Default baud rate	115200
Parity	None
Data bits	8
Stop bits	1
Flow control	None

Correct command formatting

Add a space between the code and the number when entering commands.

For example, PWR1 can be entered as PWR 1.

Understanding message format

Commands sent to and from 4K7-HS and 4K10-HS are formatted as simple text messages consisting of a three letter command code, an optional four letter subcode, and optional data.

Source	Format	Function	Example
From controller	(Code Data)	SET (set power on)	(PWR1) or (PWR 1)
	(Code+Subcode Data)	SET (set input port configuration)	(SIN+PORT 1)
	(Code ?)	REQUEST (what is current power state?)	(PWR?) or (PWR ?)
	(Code+Subcode ?)	REQUEST (what is current input port configuration?)	(SIN+PORT?)
From projector	(Code Data)	REPLY (power state is 1 "On")	(PWR!001 "On")
	(Code+Subcode Data)	REPLY (input port configuration is 1 "One-Port")	(SIN+PORT!001 "One-Port")

Available message types

Message type	Description
Set	A command to set a projector parameter at a specific level, such as changing the brightness.
Request	A request for information, such as what is the current brightness setting.
Reply	Returns the data in response to a request or as confirmation of a command.

Message structure

Understand the components of an ASCII command.

Regardless of message type or origin, all messages use the same basic format and code. Opening and closing round brackets (parentheses) surround each message.

Message element	Description
Parentheses	Commands are enclosed by parentheses (). If a start character is received before an end character of the previous message, the partial (previous) message is discarded.

Message element	Description
Prefix characters (optional)	Acknowledges the projector has responded or increases message integrity when added before the three-character function code. <ul style="list-style-type: none"> Number symbol (#)—Request a full acknowledgment. A full acknowledgment sends an echo of the message as a reply from the projector when it finishes processing the command. Do not include a full acknowledgment in a request message.
Function code	The primary projector function being queried or modified. Each function code is represented by a three-character, upper or lower case ASCII code (A-Z). The function code appears after the first parenthesis. If a command does not include a subcode, a space between the function code and the first parameter (or special character) is optional.
+subcode	The secondary projector function being queried or modified. Each subcode is represented by a four-character, upper or lower case ASCII code (A-Z and 0-9). The subcode appears after the function code, and it is separated from the function code with a plus symbol (+). If a subcode is not included, the plus symbol is not required. If a command includes a subcode, a space between the subcode and the first parameter (or special character) is optional.
Request and reply symbols	The question mark symbol (?) appears after the function code when the controller requests projector information. An exclamation mark (!) appears after the function code when the projector responds to a request. Do not include a question or exclamation mark when creating a SET command.

Error messages

If a command cannot be performed, a descriptive error identifying the problem appears.

For example, the following message indicates a syntax error:

```
(ITP) - (65535 00000 ERR00005 "ITP: Too Few Parameters")
```

Serial API commands

The 4K7-HS and 4K10-HS commands can be used to modify product settings.

ADR–Projector Address

Sets or queries the device address.

This command also helps to identify where a response or asynchronous message originates from. Generally, this command is used for projectors that are daisy-chained together using the RS232 style communication.

The projector responds to IR remotes set to the same address as the projector or to IR remotes set to address 0.

Commands

Command		Values
ADR?	Checks the current projector address. (Read-only)	—
ADR <value>	Sets the projector address to <value>.	0 to 9 0 (Default)

Examples

Set the projector address 0:

(ADR 0)

APW–Auto Power On

Automatically turns on the projector when electrical power is connected.

Commands

Command	Description	Values
APW <0 1>	Automatically powers up the projector to the on state.	0 = Disables auto power up (Default) 1 = Enables auto power up

Examples

Turn off auto power:

(APW 0)

Turn on auto power:
(APW 1)

ASH–Auto Shutdown

Powers off the projector after a set period of time.

If an active signal is received before the projector powers down, the image is displayed.

Commands

Command	Description	Values
ASH <value>	Enables or disables auto shutdown.	0 = Turns off auto shutdown (Default) 1 = Activates auto shutdown after five minutes 2 = Activates auto shutdown after 10 minutes 3 = Activates auto shutdown after 15 minutes 4 = Activates auto shutdown after 20 minutes 5 = Activates auto shutdown after 25 minutes 6 = Activates auto shutdown after 30 minutes

Examples

Turn off auto shutdown:
(ASH 0)

Activate auto shutdown after ten minutes:
(ASH 2)

AWF–Auto Warp Filter

Automatically corrects the distorted image.

Image distortion is caused by projection to a curved surface or by lens distortion.

Commands

Command	Description	Values
AWF <0 1>	Enables or disables automatically applying a preset warp filter for image distortion correction.	0 = Disables automatic warping 1 = Enables automatic warping (Default)

Examples

Disable automatic applying of a preset warp filter:

(AWF 0)
Enable automatic applying of a preset warp filter:
(AWF 1)

BDR–Baud Rate

Sets the baud rate for a serial communications port.

Commands

Command	Description	Values
BDR?	Returns the baud rate for the serial port. (Read-only)	—
BDR <value>	Sets the baud rate for the serial port.	0 = 1200 1 = 2400 2 = 4800 3 = 9600 4 = 14400 5 = 19200 6 = 38400 7 = 57600 8 = 115200 (Default)

Examples

Get the baud rate for the serial port: (BDR?) Result: (BRD! "115200")
Set the baud rate on port A to 115200 bits per second: (BDR+PRTA 8)

BGC–Base Gamma Curve

Selects a gamma correction curve.

Commands

Command	Description	Values
BGC <value>	Selects a gamma correction curve.	0 = Video input 1 = Film input 2 = Bright content

Command	Description	Values
		3 = Computer input (CRT) 4 = DICOM

Examples

Select a gamma correction curve for film input: (BGC 1)
Select a gamma correction curve for bright content: (BGS 2)

BOG–Blue Gain

Adds an offset to input blue gain settings of an image.

Adjusting this setting also affects the black and white components of an image.

Commands

Command	Description	Values
BOG <value>	Sets the blue gain value.	0 to 100 50 (Default)

Examples

Set the blue gain value to 50: (BOG 50)
--

BOO–Blue Offset

Adjusts the blue offset of an image.

Adjusting this setting also affects the black and white components of an image.

Commands

Command	Description	Values
BOO <value>	Sets the blue offset value.	0 to 100 50 (Default)

Examples

Set the blue offset value to 50:

(BOO 50)

BRT–Brightness

Adjust the intensity of the image.

Commands

Command	Description	Values
BRT <value>	Adjusts the intensity of the image.	0 to 100 50 (Default)

Examples

Set the intensity of the image to 50:

(BRT 50)

CCA–Color Matching

Defines the hue of each primary color component (red, green, blue, and white).

Commands

Command	Description	Values
CCA+BLUG <value>	Specifies the blue levels of gain.	0 to 254 127 (Default)
CCA+BLUH <value>	Specifies the blue levels of hue.	0 to 254 127 (Default)
CCA+BLUS <value>	Specifies the blue levels of saturation.	0 to 254 127 (Default)
CCA+BOFW <value>	Manually adjusts the blue portion of white.	0 to 1000 0 (Default)
CCA+BRTD	Resets the blue color settings to their defaults.	—
CCA+CRTD	Resets the cyan color settings to their defaults.	—
CCA+CYAH <value>	Specifies the cyan levels of hue.	0 to 254 127 (Default)
CCA+CYAG <value>	Specifies the cyan levels of gain.	0 to 254 127 (Default)

Command	Description	Values
CCA+CYAS <value>	Specifies the cyan levels of saturation.	0 to 254 127 (Default)
CCA+GREG <value>	Specifies the green levels of gain.	0 to 254 127 (Default)
CCA+GREH <value>	Specifies the green levels of hue.	0 to 254 127 (Default)
CCA+GRES <value>	Specifies the green levels of saturation.	0 to 254 127 (Default)
CCA+GRTD	Resets the green color settings to their defaults.	—
CCA+HSGE <0 1>	Turns hue, saturation, and gain (HSG) adjustments. The HSG function independently controls each of the color regions R, G, B, C, M, Y, and W.	0 = Turns off HSG adjustments (Default) 1 = Turns on HSG adjustments
CCA+MAGG <value>	Specifies the magenta levels of gain.	0 to 254 127 (Default)
CCA+MAGH <value>	Specifies the magenta levels of hue.	0 to 254 127 (Default)
CCA+MAGS <value>	Specifies the magenta levels of saturation.	0 to 254 127 (Default)
CCA+MHTP <0 1>	Turns automatic test patterns for HSG adjustment items on or off.	0 = Turns off automatic test patterns 1 = Turns on automatic test patterns (Default)
CCA+MRTD	Resets the magenta color settings to their defaults.	—
CCA+REDG <value>	Specifies the red levels of gain.	0 to 254 127 (Default)
CCA+REDH <value>	Specifies the red levels of hue.	0 to 254 127 (Default)
CCA+REDS <value>	Specifies the red levels of saturation.	0 to 254 127 (Default)
CCA+RRTD	Resets the red color settings to their defaults.	—
CCA+WALL <0 1 2>	Sets the wall color so the projector can enhance the color performance customized for the specific wall.	0 = White (Default) 1 = Gray 130 2 = Light yellow
CCA+WHBG <value>	Specifies the blue levels of white gain.	0 to 254 127 (Default)
CCA+WHGG <value>	Specifies the green levels of white gain.	0 to 254

Command	Description	Values
		127 (Default)
CCA+WHRG <value>	Specifies the red levels of white gain.	0 to 254 127 (Default)
CCA+WRTD	Resets the white gains settings to their defaults.	—
CCA+YELG <value>	Specifies the yellow levels of gain.	0 to 254 127 (Default)
CCA+YELH <value>	Specifies the yellow levels of hue.	0 to 254 127 (Default)
CCA+YELS <value>	Specifies the yellow levels of saturation.	0 to 254 127 (Default)
CCA+YRTD 1	Resets the yellow color settings to their defaults.	1

Examples

Set the red level of hue to 120: (CCA+REDH 120)
Turn on automatic test patterns for HSG adjustments: (CCA+MHTP 1)
Set the wall color to white: (CCA+WALL 1)

CCI–Color Temperature

Applies a predefined color temperature value to the input signal.

Commands

Command	Description	Values
CCI <value>	Applies a color temperature to the input signal.	0 = Warmest 1 = Warm 2 = Cool (Default)

Examples

Apply the warmest color temperature: (CCI 0)
Apply the cool color temperature:

(CCI 2)

CEL–Ceiling Mount Setting

Changes the image orientation of ceiling mounted projectors.

Commands

Command	Description	Values
CEL <value>	Changes the image orientation of ceiling mounted projectors.	0 = Turns off the ceiling mount setting 1 = Turns on the ceiling mount setting and turns the image upside down 2 = Automatically adjusts image orientation to the projector position (Default)

Examples

Turn off the ceiling mount setting: (CEL 0)
Turn on the ceiling mount setting and turns the image upside down: (CEL 1)
Automatically adjust the image orientation to the projector position: (CEL 2)

CNR–4-Corner Geometry Correction

Fits an image in an area defined by x and y coordinates.

Commands

Command	Description	Values
CNR+BLCX <value>	Applies a bottom left horizontal adjustment, in pixels.	0 to 120 0 (Default)
CNR+BLCY <value>	Applies a bottom left vertical adjustment, in pixels.	0 to 80 0 (Default)
CNR+BRCX <value>	Applies a bottom right horizontal adjustment, in pixels.	0 to 120 0 (Default)
CNR+BRCY <value>	Applies a bottom right vertical adjustment, in pixels.	0 to 80 0 (Default)
CNR+RSET 1	Resets the adjustments to the defaults.	1

Command	Description	Values
CNR+TLCX <value>	Applies a top left horizontal adjustment, in pixels.	0 to 120 0 (Default)
CNR+TLCY <value>	Applies a top left vertical adjustment, in pixels.	0 to 80 0 (Default)
CNR+TRCX <value>	Applies a top right horizontal adjustment, in pixels.	0 to 120 0 (Default)
CNR+TRCY <value>	Applies a top right vertical adjustment, in pixels.	0 to 80 0 (Default)

Examples

Set the top-left vertical adjustment value to 20:
(CNR+TLCY 20)

CON–Contrast

Sets the image contrast by adjusting the gain applied to the input signal.

This command adjusts the degree of difference between the lightest and darkest parts of the image and changes the amount of black and white in the image.

Commands

Command	Description	Values
CON <value>	Sets the degree of difference between the lightest and darkest parts of the image and changes the amount of black and white in the image.	0 to 100 50 (Default)

Examples

Set the contrast value to 50:
(CON 50)

CSP–Color Space

Specifies which color space the input signal uses.

This command is only useful for analog signals and certain digital sources.

Commands

Command	Description	Values
CSP <value>	Selects the color space for the input signal.	0 = Auto For RGB: 1 = RGB Full (Default) 2 = RGB Limited For YUV: 3 = REC709 (Default) 4 = REC601

Examples

Select the RGB color space for the input signal:
(CSP 1)

CWI–Wheel Index Setting

Adjusts the phosphor and filter wheels.

This command can only be run when the projector is in service mode.

Commands

Command	Description	Values
CWI+PF2x <index>	Sets the speed of the phosphor wheel index to 2x.	0 to 719
CWI+FT2x <index>	Sets the speed of the filter wheel index to 2x.	

Examples

Set the speed of phosphor wheel index 26 to 2x:
(CWI+PF2X 26)

DEF–Factory Defaults

Resets 4K7-HS and 4K10-HS to its factory default values.

Commands

Command	Description	Values
DEF 111	Restores all settings to the factory defaults.	111

Command	Description	Values
	To prevent accidental use of this command, the number 111 must follow the command.	

Examples

Reset 4K7-HS and 4K10-HS to factory defaults:
(DEF 111)

DIM–Contrast Enhancement

Enables or disables the automatic adjustment for the black values of the displayed image.

Commands

Command	Description	Values
DIM <value>	Enables or disables dynamic black and real black.	0 = Turns off dynamic black (Default) 1 = Turns on dynamic black 2 = Turns on real black

Examples

Turn on dynamic black:
(DIM 1)

DSH–Digital Horizontal Shift

Moves the projector image left or right. If the image is not zoomed out (Digital Zoom), this command is disabled.

Commands

Command	Description	Values
DSH <value>	Moves the projector to the left or right.	0 to 100 0 = Moves the display area to the extreme left 50 = Centers the display area horizontally (Default) 100 = Moves the display area to the extreme right

Examples

Center the display area horizontally:
(DSH 50)

DSV–Digital Vertical Shift

Moves the projector image up or down. If the image is not zoomed out (Digital Zoom), this command is disabled.

Commands

Command	Description	Values
DSV <value>	Moves the projector to the up or down.	0 to 100 0 = Moves the display area to the top 50 = Centers the display area vertically (Default) 100 = Moves the display area to the bottom

Examples

Center the display area vertically:
(DSV 50)

DTL–Detail

Selects the edge clarity of the image.

Commands

Command	Description	Values
DTL <value>	Selects the edge clarity of the image.	0 = Maximum 1 = High 2 = Normal (Default) 3 = Low 4 = Minimum

Examples

Set the edge clarity of the image to high:
(DTL 1)

DZH–Digital Horizontal Zoom

Changes the size of the horizontal display area.

If the display area has been resized with this setting, use the DSH–Digital Horizontal Shift and DSV–Digital Vertical Shift commands to readjust the image.

Commands

Command	Description	Values
DZH <value>	Changes the size of the horizontal display area.	50% to 400% 100% (Default)

Examples

Change the horizontal size of the display area to 100%:
(DZH 100)

DZV–Digital Vertical Zoom

Changes the size of the vertical display area.

If the display area has been resized with this setting, use the DSH–Digital Horizontal Shift and DSV–Digital Vertical Shift commands to readjust the image.

Commands

Command	Description	Values
DZV <value>	Changes the size of the vertical display area.	50% to 400% 100% (Default)

Examples

Change the vertical size of the display area to 100%:
(DZV 100)

EBL–Edge Blending

Creates a single image from a multi-projector installation.

Commands

Command	Description	Values
EBL+BTME <0 1>	Enables or disables edge blending of the bottom edge.	0 = Disables edge blending of the bottom edge (Default) 1 = Enables edge blending of the bottom edge
EBL+BTMS <value>	Sets the starting point of the bottom edge blend.	0 to 400 pixels 0 (Default)
EBL+BTMW <value>	Sets the height of the bottom edge blend.	4 to 1000 pixels

Command	Description	Values
		4 (Default)
EBL+GAMA	Sets the gamma value for blending.	0 = 1.8 1 = 1.9 2 = 2.0 3 = 2.1 4 = 2.2 (Default) 5 = 2.3 6 = 2.4
EBL+LFTE <0 1>	Enables or disables edge blending of the left edge.	0 = Disables edge blending of the left edge (Default) 1 = Enables edge blending of the left edge
EBL+LFTS <value>	Sets the starting point of the left edge blend.	0 to 400 pixels 0 (Default)
EBL+LFTW <value>	Sets the height of the left edge blend.	4 to 1600 pixels 4 (Default)
EBL+RHTE <0 1>	Enables or disables edge blending of the right edge.	0 = Disables edge blending of the right edge (Default) 1 = Enables edge blending of the right edge
EBL+RHTS <value>	Sets the starting point of the right edge blend.	0 to 400 pixels 0 (Default)
EBL+RHTW <value>	Sets the height of the right edge blend.	4 to 6000 pixels 4 (Default)
EBL+TOPE <0 1>	Enables or disables edge blending of the top edge.	0 = Disables edge blending of the top edge (Default) 1 = Enables edge blending of the top edge
EBL+TOPS <value>	Sets the starting point of the top edge blend.	0 to 400 pixels 0 (Default)
EBL+TOPW <value>	Sets the height of the top edge blend.	4 to 1000 pixels 4 (Default)

Examples

Turn on the bottom edge blending: (EBL+BTME 1)
Set the left edge blending starting point to 150 pixels: (EBL+LFTS 150)
Set the top blend height to 200 pixels: (EBL+TOPW 200)

ERR–Error Log

Displays or clears the error log.

Commands

Command	Description	Values
ERR?	Shows the error log. (Read-only)	—
ERR+CLER 1	Clears the error log.	1

Examples

Show the error log: (ERR?)
Clear the error log: (ERR+CLER 1)

FAN–Fan Info

Displays the information of each fan.

Commands

Command	Description	Values
FAN+FA01?	Displays information for fan 1. (Read-only)	—
FAN+FA02?	Displays information for fan 2. (Read-only)	—
FAN+FA03?	Displays information for fan 3. (Read-only)	—
FAN+FA04?	Displays information for fan 4. (Read-only)	—
FAN+FA05?	Displays information for fan 5. (Read-only)	—
FAN+FA06?	Displays information for fan 6. (Read-only)	—
FAN+FA07?	Displays information for fan 7. (Read-only)	—
FAN+FA08?	Displays information for fan 8. (Read-only)	—
FAN+FA09?	Displays information for fan 9. (Read-only)	—
FAN+FA10?	Displays information for fan 10. (Read-only)	—

Examples

Display the information for the fan 5: (FAN+FA05)
--

FCS– Focus

Adjusts the focus of the image.

Commands

Command	Description	Values
FCS <position>	Adjusts the lens focus.	n = Increases the focus of the lens by one p = Decreases the focus of the lens by one

FCT–Serial Number

Sets the serial number for the projector.

Commands

Command	Description	Values
FCT+SERN "AAABYWNNN"	Sets the serial number for the projector.	AAABYWNNN = Serial number

FDY–Frame Delay

Corrects asynchronous displaying of images for 3D blending.

Commands

Command	Description	Values
FDY <value>	Sets the value to correct asynchronous displaying of images for 3D blending.	1 to 200 (by timing) 1 (Default)

Examples

Set the frame delay to 100:

```
(FDY 100)
```

FKC–4K Compatible

Enables or disables 4K compatibility.

Commands

Command	Description	Values
FKC <0 1>	Enables or disables 4K compatibility.	0 = Enables 4K compatibility 1 = Disables 4K compatibility (Default)

Examples

Enable 4K compatibility: (FKC 0)
Disable 4K compatibility: (FKC 1)

FRZ–Image Freeze

Freezes the active video or test pattern to allow a detailed examination of a single frame of an otherwise moving image.

Commands

Command	Description	Values
FRZ <0 1>	Freezes the active video or test pattern.	0 = Disables freezing of current video (Default) 1 = Freezes the current video

Examples

Freeze the image: (FRZ 1)

GOG–Green Gain

Adds an offset to input green gain settings of an image.

Adjusting this setting also affects the black and white components of an image.

Commands

Command	Description	Values
GOG <value>	Sets the green gain value.	0 to 100 50 (Default)

Examples

Set the green gain value to 50:
(GOG 50)

GOO–Green Offset

Adjusts the green offset of an image.

Adjusting this setting also affects the black and white components of an image.

Commands

Command	Description	Values
GOO <value>	Sets the green offset value.	0 to 100 50 (Default)

Examples

Set the green offset value to 50:
(GOO 50)

GOR–RGB Gain/Offset Reset

Resets red, green, and blue gain and offset values.

Commands

Command	Description	Values
GOR 1	Resets the red, green, and blue offset values to their default settings.	1

Examples

Reset the offset values to their default values:
(GOR 1)

HAR—Reset Hue, Saturation, and Gain to Default

Resets the hue, saturation, and gain adjustments to the default settings.

Commands

Command	Description	Values
HAR 1	Resets the hue, saturation, and gain adjustments to the default settings	1

Examples

Reset the hue, saturation, and gain adjustments to the default:

(HAR 1)

HAT—High Altitude

Increases the fan speeds to improve cooling when the projector is installed in a high altitude location.

Commands

Command	Description	Values
HAT <0 1>	Enables or disables high altitude functionality.	0 = Turns off high altitude functionality (Default) 1 = Turns on high altitude functionality

Examples

Turn on high altitude functionality:

(HAT 1)

HDR—HDR

Increases the dynamic range to see the full spectrum of the image.

In other words, after enabling this function, details are visible in the dark while the bright parts of the image are still visible.

Commands

Command	Description	Values
HDR+HDRE <0 1>	Automatically detects the HDR signal or disables the signal.	0 = Auto—Automatically detects the HDR signal 1 = Off—Disables HDR

Command	Description	Values
HDR+HDRL <value>	Determines how HDR signals are processed.	0 = SDR—Applies HDR processing effect to the SDR signal 1 = HDR1—Applies for images with richly saturated colors 2 = HDR2—Applies for images with natural colors 3 = HDR3—Applies for images requiring improved details 4 = HDR4—Applies for images requiring more details in dark scenes

Examples

Automatically detect the HDR signal: (HDR+HDRE 0)
Disable detecting the HDR signal: (HDR+HDRE 1)
Apply HDR processing for images with natural colors: (HDR+HDRL 2)

HKS—Hot Key Settings

Assigns different functions to the infrared remote hot key.

Commands

Command	Description	Values
HKS <value>	Assigns different functions to the infrared remote hot keys.	0 = Adjusts the aspect ratio 1 = Displays the picture settings 2 = Resets to the default values 3 = Selects the edge clarity of the image 4 = Enables or disables dynamic black and real black 5 = Sets the light source and intensity modes 6 = Freezes the image 7 = Display projector information

Examples

Set the infrared remote hot key to freeze the screen: (HKA 6)
--

HOR–Horizontal Position

Moves the horizontal position of the image left or right.

When applying this function, some of the active area is blank. Increase the value to move the active image to the right.

Commands

Command	Description	Values
HOR?	Returns the horizontal position value on the main video. (Read-only)	—
HOR <value>	Sets the horizontal position for the main image.	0 to 100 50 (Default)

Examples

Move the starting point of the input capture to 50:

(HOR 50)

HPC–Horizontal Pincushion

Corrects the distortion created when the left and right sides of the image bends inwards to the center of the display.

Commands

Command	Description	Values
HPC <value>	Adjusts the horizontal distortion value.	0 to 100 50 (Default)

Examples

Adjust the horizontal distortion to the default:

(HPC 50)

HSG–Color Enhancement

Applies preset color enhancements.

Commands

Command	Description	Values
HSG <value>	Applies a present color enhancement.	0 = Turns off color enhancement (Default) 1 = Applies color enhancement mode 1 (more natural) to the input signal 2 = Applies color enhancement mode 2 (more vivid) to the input signal

Examples

Turn off color enhancement: (HSG 0)
Apply color enhancement mode 1: (HSG 1)
Apply color enhancement mode 2: (HSG 2)

ICI–Communications Info

Displays the current settings for the communication information such as the projector's IP address, subnet, and so on.

Returns communications information in read-only mode.

Commands

Command	Description	Values
ICI?	Displays the current settings for the communication information.	—

Examples

Return the communication information: (ICI?)

ILI–Light Source Info

Displays the light source information such as projector hours and laser diode (LD) hours.

Commands

Command	Description	Values
ILI?	Displays the light source information.	—

Examples

Return the light source information:
(ILI?)

IRC–IR Control

Enables or disables the IR sensors.

Commands

Command	Description	Values
IRC+FRNT <0 1>	Enables or disables the signal from the front IR sensor.	0 = Disables the signal from the front IR sensor 1 = Enables the signal from the front IR sensor (Default)
IRC+HDBT <0 1>	Enables or disables the signal from the HDBaseT box.	0 = Disables the signal from the HDBaseT box 1 = Enables the signal from the HDBaseT box (Default)
IRC+TOPP <0 1>	Enables or disables the signal from the top IR sensor.	0 = Disables the signal from the top IR sensor 1 = Enables the signal from the top IR sensor (Default)

Examples

Enable the signal from the front IR sensor:
(IRC+FRNT 1)

Disable the sensor from the HDBaseT box:
(IRC+HDBT 0)

Disable the signal from the top IR sensor:
(IRC+TOPP 0)

ITP–Test Pattern

Displays a test pattern.

Commands

Command	Description	Values
ITP <pattern>	Displays a test pattern on the display.	0 = Off (Default) 1 = Grid 2 = White 3 = Black 4 = Checkerboard 5 = Color bar 6 = Red 7 = Green 8 = Blue 9 = Yellow 10 = Magenta 11 = Cyan 12 = Boresight 13 = FullScreen

Examples

Disable test patterns and revert to the previous input signal:

```
(ITP 0)
```

Set the test pattern to the grid pattern:

```
(ITP 1)
```

KBL–Keypad Backlight

Determines if the keypad is backlit or not and for how long.

Commands

Command	Description	Values
KBL <value>	Sets how long the keypad stays backlit.	0 = Stays backlit for 5 seconds (Default) 1 = Stays backlit for 10 seconds 2 = Stays backlit for 20 seconds 3 = Stays backlit for 30 seconds 4 = Keeps the keypad constantly backlit 5 = Disables the backlight feature

Examples

Backlight the keypad for 20 seconds: (KBL 2)
Disable the backlight feature: (KBL 0)

KEY–Key Mode Emulator

Uses key codes to emulate button presses on the infrared remotes or wired keypads.

Commands

Command	Description	Values
KEY <number>	Sends the command associated with the key to the product. (Read-only)	number = Menu key number

Examples

Send menu key 17 to the projector and displays the menu on the on-screen display: (KEY 17)

LCB–Lens Motor Calibration

Calibrates the lens mount system for each of the four lens axes (horizontal, vertical, zoom, and focus) to determine home positions, the motor travel ranges, and the motor backlash values.

Commands

Command	Description	Values
LCB+HOME 0	Moves the lens to the center and horizontal and vertical position. Zoom and focus are not affected.	0
LCB+LOCK <0 1>	Locks the zoom, focus, horizontal, and vertical lens motors. This helps to prevent accidental lens position changes in multi-projector installations.	0 = Allows movement of the zoom, focus, horizontal, and vertical lens motors (Default) 1 = Locks the zoom, focus, horizontal, and vertical lens motors

Examples

Center the lens: (LCB+HOME 0)

Lock the zoom, focus, horizontal, and vertical lens motors:
(LCB+LOCK 1)

LCE—Last Serial Command Error

Displays the last serial command error.

Commands

Command	Description	Values
LCE?	Returns the last serial command error. (Read-only)	—

LDI—Laser Diode Information

Displays the information of each laser diode bank including its voltage and temperature.

Commands

Command	Description	Values
LDI+LD01?	Displays the voltage, current, and temperature status for laser diode 1. (Read-only)	—
LDI+LD02?	Displays the voltage, current, and temperature status for laser diode 2. (Read-only)	—
LDI+LD03?	Displays the voltage, current, and temperature status for laser diode 3. (Read-only)	—
LDI+LD04?	Displays the voltage, current, and temperature status for laser diode 4. (Read-only)	—
LDI+LD05?	Displays the voltage, current, and temperature status for laser diode 5. (Read-only)	—
LDI+LD06?	Displays the voltage, current, and temperature status for laser diode 6. (Read-only)	—
LDI+LD07?	Displays the voltage, current, and temperature status for laser diode 7. (Read-only)	—
LDI+LD08?	Displays the voltage, current, and temperature status for laser diode 8. (Read-only)	—
LDI+LD09?	Displays the voltage, current, and temperature status for laser diode 9. (Read-only)	—
LDI+LD10?	Displays the voltage, current, and temperature status for laser diode 10. (Read-only)	—
LDI+LD11?	Displays the voltage, current, and temperature status for laser diode 11. (Read-only)	—
LDI+LD12?	Displays the voltage, current, and temperature status for laser diode 12. (Read-only)	—

Examples

Display the information for the laser diode bank 1:
(LDI+LD01)

LET–Lens Type

Sets the correct lens type to have the correct offset range.

Commands

Command	Description	Values
LET <value>	Sets the correct lens type to have the correct offset range.	0 = Undefined lens 1 = 1.2-1.5:1 zoom lens 2 = 1.5-2.0:1 zoom lens 3 = 2.0-4.0:1 zoom lens 4 = 4.0-7.2:1 zoom lens 5 = 0.85-1.02:1 short zoom lens 6 = 1.20-1.73 4K short zoom lens

Examples

Set the lens type to the 1.2-1.5:1 zoom lens: (LET 1)
Set the lens type to the 1.5-2.0:1 zoom lens: (LET 3)
Set the lens type to the 1.20-1.73 4K short zoom lens: (LET 6)

LHO–Lens Shift Horizontal

Adjusts the horizontal lens offset.

Commands

Command	Description	Values
LHO <position>	Adjusts the horizontal location of the lens.	n = Increases horizontal location of the lens by one p = Decreases horizontal location of the lens by one

LLM—Low Latency Mode

Enables or disables the low latency mode for streaming media to minimize the input lag.

Commands

Command	Description	Values
LLM <0 1>	Enables or disables low latency mode.	0 = Disables low latency mode (Default) 1 - Enables low latency mode

Examples

Disable low latency mode: (LLM 0)
Enable low latency mode: (LLM 1)

LRR—L/R Reference

Sets the left/right (L/R) reference for the projector.

Commands

Command	Description	Values
LRR "<value>"	Sets the left/right (L/R) reference for the projector.	1st Frame = Sets the first frame from the input source as the left reference (Default) Field GPIO = Sets the field GPIO of the input source as the left and right reference

Examples

Set the first frame from the input source as the left reference: (LRR "1st Frame")
Set the field GPIO of the input source as the left and right reference: (LRR "Field GPIO")

LMA–Lens Memory Apply Position

Applies the lens position according to the chosen lens memory position.

Commands

Command	Description	Values
LMA <value>	Applies the lens position according to the chosen lens memory position.	0 to 4

Examples

Set the lens position to the value stored in record 2:

(LMA 1)

Set the lens position to the value stored in record 5:

(LET 4)

LMS–Lens Memory Save Current Position

Saves the current lens position to the projector memory.

Commands

Command	Description	Values
LMS <value>	Saves the current lens position to the projector memory.	0 to 4

Examples

Save the lens position to the value stored in record 1:

(LMS 0)

Save the lens position to the value stored in record 4:

(LET 3)

LOC–Localization Language

Sets the language for the on-screen display (OSD).

Commands

Command	Description	Values
LOC+LANG <value>	Sets the on-screen display language.	0 = English (Default) 1 = Simplified Chinese

Command	Description	Values
		2 = French 3 = German 4 = Italian 5 = Japanese 6 = Korean 7 = Russian 8 = Spanish

Examples

Set the language to French: (LOC+LANG 2)
Set the language to Russian: (LOC+LANG 7)

LOL–Lights Out Signal Level

Sets the signal level for lights out for the RealBlack feature.

Commands

Command	Description	Values
LOL <value>	Sets the lights out signal level.	0 to 5 0 (Default)

Examples

Set the signal level to 4: (LOL 4)

LOT–Lights Out Timer

Sets a timer for lights out for the RealBlack feature.

Commands

Command	Description	Values
LOT <value>	Sets the lights out timer.	0 to 20 0 (Default)

Examples

Set a timer to turn off the lights in 20 seconds:
(LOT 20)

LPM—Light Source Mode

Sets the light source and intensity modes.

Commands

Command	Description	Values
LPM <value>	Sets the light source mode.	0 = Constant Power—Specifies the power level supplied (Default) 1 = Constant Intensity—Maintains a specific brightness level over time 2 = Eco Mode—Maintains brightness at 80% for as long as possible 3 = Eco Mode—Maintains brightness at 50% for as long as possible 4 = Rental Mode—Adjusts to the lowest fan speed and switches the laser diode power to the minimum setting

Examples

Maintain the light source with 50% brightness for as long as possible:
(LPM 3)

LPP—Constant Power

Sets the value of the laser diode power.

Commands

Command	Description	Values
LPP <power>	Sets the value of the laser diode power.	1 (30%) to 100 (100%) 100 (Default)

Examples

Set the laser diode power to 30%:
(LPP 1)

LSE—Last System Error

Retrieves the last recorded system error.

Commands

Command	Description	Values
LSE?	Displays the last system error. (Read-only)	1 = The light source did not engage after five attempts 3 = The light source went out unexpectedly 4 = Fan failure 5 = Over temperature

LVO—Lens Shift Vertical

Adjusts the vertical lens offset.

Commands

Command	Description	Values
LVO <position>	Adjusts the vertical location of the lens.	n = Increases vertical location of the lens by one p = Decreases vertical location of the lens by one

MBE—Message Box Enable

Enables or disables the displaying of groups of message boxes on the on-screen display.

Commands

Command	Description	Values
MBE+USER <0 1>	Enables or disables displaying message boxes directly triggered by user actions, for example gamma or lens control message boxes.	0 = Disables displaying message boxes directly triggered by user actions 1 = Enables displaying message boxes directly triggered by user actions (Default)

Examples

Set user message boxes to not be displayed:

(MBE+USER 0)

Result:

OFF

Set user message boxes to be displayed:

(MBE+USER 1)

Result:
ON

MIF–Main (Single) Source Information

Displays the current settings for the main image input.

Commands

Command	Description	Values
MIF+ACTS?	Returns the active source. (Read-only)	—
MIF+APRT?	Returns the aspect ratio. (Read-only)	—
MIF+CLSP?	Returns the color space setting. (Read-only)	—
MIF+HREF?	Returns horizontal refresh information. (Read-only)	—
MIF+PIXC?	Returns the pixel clock settings. (Read-only)	—
MIF+RESL?	Returns the resolution. (Read-only)	—
MIF+SGFT?	Returns the signal format. (Read-only)	—
MIF+SYNC?	Returns the sync type. (Read-only)	—
MIF+VREF?	Returns vertical refresh information. (Read-only)	—

Examples

Return the image resolution:
(MIF+RESL?)

MMC–Motion Estimate and Motion Compensation

Improves the video content being displayed.

Motion estimate and motion compensation (MEMC) is a technology used to reduce the energy in the motion-compensated residual frame. It can improve compression performance by accounting for motion of the objects in the video contents and increasing the frame rate from 50 or 60Hz to 100 or 120Hz.

Commands

Command	Description	Values
MMC+COLR <value>	Adjusts the color to increase the reproduction of the video content.	0 = Off 1 to 5= Adjusts the color

Command	Description	Values
MMC+DEMO <value>	Splits the screen either horizontally or vertically so the user can see the difference in the image quality between unprocessed content and content processed by MEMC.	0 = Off 1 = H split—Splits the screen horizontally 2 = V Split—Splits the screen vertically
MMC+DTIL <value>	Adjusts the brightness of the display during dark and bright movie scenes to show the video content in details.	0 = Off 1 to 3 = Adjusts the brightness
MMC+MOTN <value>	Preserves the natural motion of the displayed image.	0 = Off 1 to 3 = Adjusts the motion

Examples

Do not preserve the natural motion of the displayed image: (MMC+MOTN 0)
Split the screen horizontally to demonstrate unprocessed content and MEMC processed content: (MMC+DEMO 1)
Increase the brightness of the display: (MMC+DTIL 3)

MSH—Menu Shift Horizontal

Moves on-screen menus and messages horizontally.

Commands

Command	Description	Values
MSH <value>	Moves the on-screen display to the left.	0 to 100 0 (Default)

Examples

Move the on-screen menu to the left: (MSH 0)

MSV–Menu Shift Vertical

Changes the vertical position of the menus.

Commands

Command	Description	Values
MSV?	Returns the current vertical position of the main menu. (Read-only)	—
MSV <value>	Sets the vertical position of the menus.	0 to 100 0 (Default)

Examples

<p>Get current vertical position of the main menu:</p> <p>(MSV?)</p> <p>Result:</p> <p>0</p>
<p>Set the main menu vertical position to 50 pixels from the center:</p> <p>(MSV 50)</p>

MTO–Menu Time Out

Adjusts the time for on-screen display to disappear.

Commands

Command	Description	Values
MTO <value>	Sets the time for the on-screen display to disappear.	0 = Off 1 = 1 minute (Default) 2 = 3 minutes

Examples

<p>Never make the on-screen display disappear:</p> <p>(MTO 0)</p>
<p>Set the on-screen display to disappear after three minutes:</p> <p>(MTO 2)</p>

MWF—Manual Warp Filter

Manually corrects the distorted image.

Image distortion is caused by projection to a curved surface or by lens distortion.

Commands

Command	Description	Values
MWF+HORZ	Adjusts the horizontal filter to correct image distortion.	0 to 9 7 (Default)
MWF+VERT	Adjusts the vertical filter to correct image distortion.	0 to 9 6 (Default)

NET—Network Setup

Modifies the network setup for this device.

Commands

Command	Description	Values
NET+DHCP <0 1>	Turns DHCP on or off.	0 = Turns on DHCP 1 = Turns off DHCP
NET+ETH0 "<value>"	Modifies Ethernet settings.	value = Ethernet address
NET+GATE "<value>"	Modifies gateway settings.	value = Default gateway
NET+HOST "<value>"	Modifies the projector name.	value = Hostname
NET+MAC0 "<value>"	Modifies the MAC address settings.	value = MAC address
NET+PDNS "<value>"	Modifies the primary DNS.	value = Primary DNS
NET+RSET 1	Returns the projector name, LAN IP address, WLAN IP address, and SNMP settings to their factory defaults. (Read-only)	1
NET+SDNS "<vale>"	Modifies the secondary DNS.	value = Secondary DNS
NET+SETT 1	Applies the network settings.	1
NET+SHOW <0 1>	Turns network messages on or off.	0 = Turns off network messages 1 = Turns on network messages
NET+SUB0 "<value>"	Modifies subnet mask settings.	value = Subnet mask

Examples

Turn DHCP off:
(NET+DHCP 1)

Set the MAC address to 00:E0:47:01:02:3C: (NET+MAC0 "00:E0:47:01:02:3C")
Turn network messages on: (NET+SHOW 1)
Set the Ethernet address to 192.168.000.001: (NET+ETH0 "192.168.000.001")
Reset to the default settings: (NET+RSET 1)
Set the subnet mask to 255.255.255.000: (NET+SUB0 "255.255.255.000")

NTW–Wireless Network

Modifies the wireless network settings.

Commands

Command	Description	Values
NTW+ENIP "<value>"	Modifies the end IP address for the wireless network.	value = Numeric value
NTW+ETH0 "<value>"	Modifies the start IP address for the wireless network.	value = Numeric value
NTW+GATE "<value>"	Modifies gateway settings.	value = Numeric value
NTW+SLCT <0 1>	Turns wireless network on or off.	0 = Turns the wireless network off 1 = Turns the wireless network on
NTW+SSID "<value>"	Modifies the unique wireless network name.	value = Numeric value
NTW+SUB0 "<value>"	Modifies subnet mask settings.	value = Numeric value

Examples

Set the IP address to 192.168.000.001: (NET+ETH0 "192.168.000.001")
Set the MAC address to 00:E0:47:01:02:3C: (NET+MAC0 "00:E0:47:01:02:3C")
Turn the wireless LAN on: (NTW+SLCT 1)
Set the subnet mask to 255.255.255.000:

(NET+SUB0 "255.255.255.000")

OSD—On Screen Display

Displays or hides the on-screen display.

Commands

Command	Description	Values
OSD?	Returns the status of the on-screen display. (Read-only)	—
OSD <0 1>	Enables or disables the on-screen display.	0 = Hides the on-screen display 1 = Displays the on-screen display

Examples

Get the current state of the on-screen display:

(OSD?)

Hide the on-screen display:

(OSD 0)

OST—OSD Transparency

Changes the transparency of on-screen menus and messages.

Commands

Command	Description	Values
OST <value>	Changes the transparency of the menus and messages.	0 to 90 0 (Default)

Examples

Turn off the transparency:

(OST 0)

PCG—Change Pin

Changes the personal identification number (PIN) on a projector.

Commands

Command	Description	Values
PCG "<00000,NNNNN>"	Replaces the existing PIN number, where: <ul style="list-style-type: none"> • 00000 = Previous PIN • NNNNN = New PIN 	Valid PIN number 12345 (Default)

Examples

Replace the default PIN number with a new PIN:
(PCG "12345,78564")

PHS—Picture-in-Picture Horizontal Size

Sets the size (width) of the picture-in-picture/picture-by-picture window.

The active portion of the input signal, as determined by blanking controls, is scaled to fit into the picture-in-picture window.

Commands

Command	Description	Values
PHS?	Displays the picture-in-picture size. (Read-only)	—
PHS <value>	Sets the picture-in-picture/picture-by-picture size.	0 = Small 1 = Medium 2 = Large (Default)

Examples

Set the picture-in-picture size to large:
(PHS 2)

PIF—Projector Information

Displays information about the projector.

This command is only available when the projector is in service mode and is read-only.

Commands

Command	Description	Values
PIF+FWV#?	Returns the version of various components. (Read-only)	1 = F-MCU 2 = F-Image 3 = M-MCU 4 = L-MCU 5 = K-MCU 6 = P=MCU 7 = LAN 8 = MStar 9 = MEMC A = Formatter B = HDBaseT
PIF+MDLN?	Returns the model name. (Read-only)	—
PIF+NERS?	Returns the native resolution. (Read-only)	—
PIF+SNUM?	Returns the serial number. (Read-only)	—
PIF+WHEE?	Returns the color wheel index. (Read-only)	—

PIP—Picture in Picture

Enables or disables picture-in-picture (PIP)/picture-by-picture (PBP) mode.

Commands

Command	Description	Values
PIP?	Returns the state of the picture-in-picture/picture-by-picture command. (Read-only)	—
PIP <value>	Enables or disables the picture-in-picture/picture-by-picture window.	0 = Disables the picture-in-picture/picture-by-picture video (Default) 1 = Enables the picture-in-picture/picture-by-picture video

Examples

Return the state of the picture-in-picture/picture-by-picture command: (PIP?)
Disable picture-in-picture/picture-by-picture video: (PIP 0)
Enable picture-in-picture/picture-by-picture video: (PIP 1)

PIV-PIN Protect

Activates password protection on the projector, where a personal identification number (PIN) must be provided before an image can be displayed.

Commands

Command	Description	Values
PIV "XXXXX"	Activates password protection on the projector.	X = 0 to 9 Replace each X with a number from 0 to 9

Examples

Set the PIN to 33445:
(PIV "33445")

PPP-Main Layout

Chooses a preset location for the picture-in-picture and picture-by-picture window.

Note the following:

- The Location settings adjust the position of the window.
- Blanking is not affected.
- While in split screen mode, several channel controls that resize image are disabled.

Commands

Command	Description	Values
PPP <value>	Selects the picture-in-picture/ picture-by-picture image location.	0 = Places the picture-by-picture image on the left vertical center of the main image (Default) 1 = Places the picture-by-picture image on the top center of the main image 2 = Places the picture-by-picture image on the right vertical center of the main image 3 = Places the picture-by-picture image on the bottom center of the main image 4 = Places the picture-in-picture image on the bottom right of the main image 5 = Places the picture-in-picture image on the bottom left of the main image 6 = Places the picture-in-picture image on the top left of the main image 7 = Places the picture-in-picture image on the top right of the main image

Examples

Set the picture-by-picture image on the bottom of the main image:

(PPP 1)

Set the picture-by-picture image on the top-left corner of the image:

(PPP 6)

PPS—Picture-in-Picture/Picture-by-Picture Swap

Swaps the current main and picture-in-picture/picture-by-picture inputs, regardless if valid signals are on either of the inputs.

Commands

Command	Description	Values
PPS	Swaps the main and picture-in-picture/picture-by-picture input.	—

Examples

Swap the main and picture-in-picture/picture-by-picture input.:

(PPS 1)

PST—Picture Setting

Changes the picture-related settings for the current source to a set of predefined values.

This command optimizes the projector display for certain conditions, such as presentation, video, 2D high speed, 3D, and so on. Applying this setting affects the following commands:

- Gamma
- Sharpness
- White peaking
- Overscan
- Brightness
- Contrast
- Color
- Tint
- Gain—red, green, blue
- Offset—red, green, blue

Commands

Command	Description	Values
PST <value>	Optimizes the projector.	0 = Video 1 = Bright (Default) 2 = Enhanced 3 = REC709 4 = DICOM SIM 5 = Blending 6 = User
PST+USER <value>	Stores the current settings to a user profile.	—

Examples

Optimize the projector for bright viewing content: (PST 1)
Optimize the projector to display DICOM SIM content: (PST 4)

PWR—Power

Changes the power state of the product.

Commands

Command	Description	Values
PWR?	Returns the power settings for the display. (Read-only)	—
PWR <0 1>	Turns the projector on or off.	0 = Turns off the projector 1 = Turns on the projector
PWR+STBM<0 1>	Places the projector in standby mode when connected to AC power	0 = 0.5 W mode—low power mode 1 = Communication mode—normal power mode (Default)

Examples

Get the projector power status: (PWR?)
Place the projector in communication mode: (PWR+STBM 1)

RLC–Light Sensor Calibration

Performs a calibration of the light sensor.

A calibration must be performed before using in Rental mode or after a laser diode driver has been replaced.

Commands

Command	Description	Values
RLC <0 1 2>	Performs a light sensor calibration.	0 = Default (Default) 1 = Auto 2 = Manual

Examples

Automatically perform a light sensor calibration:
(RLC 1)

ROG–Red Gain

Adds an offset to input red gain settings of an image.

Adjusting this setting also affects the black and white components of an image.

Commands

Command	Description	Values
ROG <value>	Sets the red gain value.	0 to 100 50 (Default)

Examples

Set the red gain value to 50:
(ROG 50)

ROO–Red Offset

Adjusts the red offset of an image.

Adjusting this setting also affects the black and white components of an image.

Commands

Command	Description	Values
ROO <value>	Sets the red offset value.	0 to 100 50 (Default)

Examples

Set the red offset value to 50:
(ROO 50)

SBL–Status LED

Turns the status LED on or off.

Commands

Command	Description	Values
SBL <value>	Turns the status LED on or off.	0 = Turns on the status LED (Default) 1 = Turns off the status LED 2 = Turns on the status LED only for warnings and errors

Examples

Enable the status LED so it is always on:
(SBL 0)

Turn on the status LED only for warnings and errors:
(SBL 2)

SEC–Serial Port Echo

Controls whether the serial port echoes characters.

Commands

Command	Description	Values
SEC <0 1>	Enables or disables the serial port character echo.	0 = Turns off the serial port character echo (Default) 1 = Turns on the serial port character echo

Examples

Disable the serial port character echo: (SEC 0)
Turn on the serial port character echo: (SEC 1)

SHU–Shutter

Opens and closes the shutter.

Commands

Command	Description	Values
SHU?	Gets the state of the shutter. (Read-only)	–
SHU <0 1>	Opens or closes the shutter.	0 = Opens the shutter 1 = Closes the shutter (Default)

Examples

Get the state of the shutter: (SHU?) Result: (SHU!0) Indicates the shutter is open.
Open the shutter: (SHU 0)
Close the shutter: (SHU 1)

SIF–Secondary Source Information

Displays the current settings for the picture-in-picture/picture-by-picture image input.

Returns secondary source information in read-only mode.

Commands

Command	Description	Values
SIF+ACTS?	Returns the active source. (Read-only)	–
SIF+APRT?	Returns the aspect ratio. (Read-only)	–

Command	Description	Values
SIF+CLSP?	Returns the color space setting. (Read-only)	—
SIF+HREF?	Returns horizontal refresh information. (Read-only)	—
SIF+PIXC?	Returns the pixel clock settings. (Read-only)	—
SIF+RESL?	Returns the resolution. (Read-only)	—
SIF+SGFT?	Returns the signal format. (Read-only)	—
SIF+SYNC?	Returns the sync type. (Read-only)	—
SIF+VREF?	Returns vertical refresh information. (Read-only)	—

Examples

Return the image resolution:
(SIF+RESL?)

SIN–Select Input

Selects the active input.

Commands

Command	Description	Values
SIN+MAIN <value>	Sets the active input for the main video.	1 = VGA
SIN+PIIP <value>	Sets the active input for the picture-in-picture video.	3 = HDMI 1 4 = HDMI 2 5 = DVI-D 8 = HDBaseT

Examples

Set the main video to DVI-D:
(SIN+MAIN 5)

Set the picture-in-picture video to HDBaseT:
(SIN+PIIP 8)

SIV–Serial Command Version

Displays the serial command version.

Commands

Command	Description	Values
SIV?	Displays the serial command version. (Read-only)	—

SKS–Source Key Function Settings

Sets the method for searching the input source.

Commands

Command	Description	Values
SKS <value>	Sets the method for searching the input source.	0 = Changes the source manually by pressing INPUT 1 = Lists all the sources and then select the appropriate input source 2 = Automatically searches the source (Default)

Examples

Change the source manually:

(SKS 0)

Automatically search the source:

(SKS 2)

SLP–Sleep Timer

Turns the projector off after a set period of time.

Timing starts when the projector is turned on, or when the sleep timer auto power off function is canceled. Automatic power off only occurs when an image is displayed.

Commands

Command	Description	Values
SLP <value>	Sets the duration of the sleep timer.	0 = Off (Default) 1 = 2 hours 2 = 4 hours 3 = 6 hours

Examples

Turn off the sleep timer:

(SLP 0)

Set the sleep timer duration to 4 hours:

(SLP 2)

SNS–Source Name Setting

Changes the source name to a user-defined name.

Subcode availability is determined by your hardware configuration.

Commands

Command	Description	Values
SNS+SRC <value>	Applies a name to the specified input.	0 = VGA 1 = BNC 2 = HDMI 1 3 = HDMI 2 4 = DVI-D 5 = DisplayPort 6 = 3G-SDI 7 = HDBaseT 8 = CVBS 9 = Presenter A = Card Reader B = Mini USB

Examples

Change the source name to DisplayPort:

(SNS+SRC 5)

SOR–Rear Projection

Selects the orientation of the displayed image.

Reverse the image so it can be projected from behind a translucent screen.

Commands

Command	Description	Values
SOR <0 1>	Enables or disables rear projection.	0 = Turns off rear projection (Default) 1 = Turns on rear projection

Examples

Turn off rear projection: (SOR 0)
Turn on rear projection: (SOR 1)

SOS–3D Sync Out

Transmits a 3D sync signal by the 3D sync output connector to the emitter or another downstream projector for 3D blending purposes.

Commands

Command	Description	Values
SOS <0 1>	Configures the 3D Sync OUT port.	0 = Configures the 3D Sync OUT port to be fed directly to a 3D emitter (Default) 1 = Configures the 3D Sync OUT port to be fed to another downstream projector

Examples

Configure the 3D Sync OUT port to fed directly to a 3D emitter: (SOS 0)
Configure the 3D Sync OUT port to fed to a downstream projector: (SOS 1)

SPP–Serial Port Path

Sets the serial port path.

Commands

Command	Description	Values
SPP <0 1>	Sets the serial port path.	0 = RS232 (Default) 1 = HDBaseT

Examples

Set the serial port path to RS232:

(SPP 0)

Set the serial port path to HDBaseT:

(SPP 1)

SPS–Splash Screen

Specifies the splash screen to display when no signal is present.

Commands

Command	Description	Values
SPS+SLCT <value>	Sets the splash screen to display.	0 = Factory logo (Default) 1 = Blue screen 2 = Black screen 3 = White screen

Examples

Set the splash screen to blue:

(SPS+SLCT 1)

Set the splash screen to the factory logo:

(SPS+SLCT 0)

SST–Projector Status

Returns status information about the projector in read-only mode.

Commands

Command	Description	Values
SST?	Returns all status items. (Read-only)	—

SZP–Size Presets

Sets the image to one of several preset size/position presets.

For all 3D input timings, only the 3D Mode size preset is available.

Commands

Command	Description	Values
SZP <value>	Sets the preset size type.	0 = Auto—Displays an image with the detected size (Default) 1 = Native—Displays the image in its native resolution 2 = 4:3—Retains the 4:3 aspect ratio 3 = LetterBox—Displays the image with black borders on the top and bottom 4 = Full Size—Fills the screen with the image (regardless of the source) 5 = Full Width—Stretches the image to the full display width and keeps the aspect ratio 6 = Full Height—Stretches the image to the full display height and keeps the aspect ratio 7 = Custom—Displays the image with a custom size and position for each source 8 = 3D Mode—Enabled for 3D input timings

Examples

Set the size preset to LetterBox:
 (SZP 3)

TDE–3D Enable

Sets the decoding method for 3D timings with different kinds of packing formats.

Commands

Command	Description	Values
TDE <value>	Sets the decoding method for 3D timings with different kinds of packing formats.	0 = Auto (Default) 1 = Frame Packing 2 = Side by Side 3 = Top and Bottom 4 = Frame Sequential 5 = Off

Examples

Set the decoding method for 3D timings to Frame Packing:
 (TDE 1)

TDI–3D Invert

Enables or disables inverting the 3D sequence in the case of a left and right eye mismatch.

Commands

Command	Description	Values
TDI <0 1>	Enables or disables inverting the 3D sequence in the case of a left and right eye mismatch.	0 = Turns off inverting the 3D sequence (Default) 1 = Turns on inverting the 3D sequence

Examples

Turn off inverting the 3D sequence: (TDI 0)
Turn on inverting the 3D sequence: (TDI 1)

UID–Enter Service Mode

Puts the projector in service mode.

Commands

Command	Description	Values
UID "service,service"	Places the projector in service mode.	—

Examples

Place the projector in service mode: (UID "service" "service")

VPC–Vertical Pincushion

Corrects the distortion created when the top and bottom sides of the image bend inwards to the center of the display.

If a DPWM is installed use the pincushion/barrel function for adjustments.

Commands

Command	Description	Values
VPC <value>	Sets the vertical distortion value.	0 to 100

Command	Description	Values
		50 (Default)

Examples

Set the vertical distortion value to 25:
(VPC 25)

VRT–Vertical Position

Sets the vertical position of the image.

When applying this function, some of the active area is blank. Increase the value to move the active image up.

Commands

Command	Description	Values
VRT?	Returns the vertical position value on the main video. (Read-only)	—
VRT <value>	Sets the vertical position for the main image.	0 to 100 50 (Default)

Examples

Set the vertical position to 50:
(VRT 50)

WAP–Apply Warp Settings

Applies previously saved geometry setting to the projector.

Commands

Command	Description	Values
WAP?	Returns the geometry setting that is applied to the projector.	—
WAP <value>	Applies previously saved geometry setting to the projector.	(Default) 1 to 5 = Selects saved warp settings

Examples

Disable warping:

```
(WAP 0)
Use saved warp setting #3:
(WAP 3)
```

WAS—Save Warp Settings

Saves the geometry correction after doing warping and blending.
One projector can save up to five geometry settings.

Commands

Command	Description	Values
WAS <value>	Saves the geometry correction after doing warping and blending.	0 to 4 = Saves geometry correction to one of five warp settings 0 (Default)

Examples

```
Save the geometry correction to warp setting #4:
(WAS 4)
```

WPK—White Peaking

Increases the brightness of whites to near 100%.
This setting can only be applied to video sources.

Commands

Command	Description	Values
WPK?	Returns the white peak setting that is set.	—
WPK <value>	Sets the white peak.	0 to 100 in increments of 10 steps 100 (Default)

Examples

```
Set the white peak to 50:
(WPK 50)
```

WRE–Warping Reset

Resets the geometry correction.

Commands

Command	Description	Values
WRE 1	Resets the geometry correction.	1

Examples

Reset the geometry correction:

(WRE 1)

WRP–Geometry Correction

Applies a geometry correction to an image.

Commands

Command	Description	Values
WRP+HKST <value>	Corrects image distortion created when the projected image is to the left or right of the lens axis. Increase the value to increase right keystoneing.	0 to 40 20 (Default)
WRP+VKST <value>	Corrects the distortion created when the projected image is above or below the lens axis. Increase the value to increase positive keystoneing.	0 to 40 20 (Default)

Examples

Set the horizontal keystone value to 10:

(WRP+HKST 10)

ZOM–Zoom

Sets the lens zoom.

Commands

Command	Description	Values
ZOM <value>	Increases or decreases the zoom.	n = Increases zoom by one p = Decreases zoom by one

Corporate offices

Christie Digital Systems USA, Inc.
Cypress
ph: 714 236 8610

Christie Digital Systems Canada Inc.
Kitchener
ph: 519 744 8005

Worldwide offices

Australia
ph: +61 (0) 7 3624 4888

Brazil
ph: +55 (11) 2548 4753

China (Beijing)
ph: +86 10 6561 0240

China (Shanghai)
ph: +86 21 6278 7708

France
ph: +33 (0) 1 41 21 44 04

Germany
ph: +49 2161 664540

India
ph: +91 (080) 6708 9999

Japan (Tokyo)
ph: 81 3 3599 7481

Korea (Seoul)
ph: +82 2 702 1601

Mexico
ph: +52 55 4744 1790

Republic of South Africa
ph: +27 (0)11 510 0094

Russian Federation
and Eastern Europe
ph: +36 (0) 1 47 48 100

Singapore
ph: +65 6877 8737

Spain
ph: +34 91 633 9990

United Arab Emirates
ph: +971 4 3206688

United Kingdom
ph: +44 (0) 118 977 8000

United States (Arizona)
ph: 602 943 5700

United States (New York)
ph: 646 779 2014

Independant sales consultant offices

Italy
ph: +39 (0) 2 9902 1161



For the most current technical documentation, visit www.christiedigital.com.

